

5AC324
1-MICRON CHMOS EPLD

- **High-Performance LSI Semi-Custom Logic Alternative to Low-end Gate Arrays, TTL, 74HC SSI and MSI Logic, and PLDs**
 - **High Speed t_{PD} 25 ns, 66 MHz Performance Pipelined, 33.3 MHz w/ Feedback**
 - **24 Macrocells with Programmable I/O Architecture; Up to 36 Inputs (12 Dedicated, 24 I/O)**
 - **10 Programmable Inputs Configurable as Latches, Registers, or Flow-Through**
 - **1 Flow-Through Input or Global CLK Pin; 1 Flow-Through Input or Global ILE/ICLK Pin**
 - **Programmable AND, Allocatable OR Design Allows up to 16 P-Terms per Macrocell**
 - **Software-Supported P-Term Allocation Between Adjacent Macrocells**
 - **Programmable Output Registers Configurable as D, T, JK, or SR Types**
 - **Dual Feedback on All Macrocells for Implementing Buried Registers with Bidirectional I/O**
 - **2 P-Terms on All Macrocell Control Signals**
 - **Programmable Low-Power Option for "Stand-by" Operation; 150 μ A Typical Standby Current**
 - **UV Erasable (CerDIP) EPROM Technology or OTP. 100% Generically Testable EPROM Logic Control Array**
 - **Programmable Security Bit Allows 100% Protection of Proprietary Designs**
 - **JEDEC Pinout**
 - **Available in 40-pin CerDIP/PDIP and 44-Pin PLCC Packages**
- (See Packaging Spec., Order Number #231369)




Figure 1. 5AC324 Pinout Diagrams

INTRODUCTION

The Intel 5AC324 CHMOS EPLD (Erasable Programmable Logic Device) is a high integration device that overcomes the primary limitations of standard PLDs. Due to a proprietary I/O architecture and macrocell structure, the 5AC324 is capable of implementing high performance logic functions more effectively than previously possible. The 5AC324 can be used as an alternative to low-end gate arrays, multiple programmable logic devices, or LS-, HC-, or HCT SSI and MSI logic devices. Input and macrocell features for the 5AC324 are a superset of features offered on other PLD-type products.

The 5AC324 uses advanced CHMOS EPROM cells as logic control elements instead of poly-silicon fuses. This technology allows the device to operate at levels necessary in high performance systems while significantly reducing power consumption. Its programmable standby mode reduces power to near zero in applications where a slight speed loss is traded for power savings.

ARCHITECTURE DESCRIPTION

The architecture of the 5AC324 is based on the familiar "Sum-Of-Products" programmable AND, fixed OR structure. This structure is then surrounded by powerful, programmable macrocells and inputs. The 5AC324 can implement both combinatorial and sequential logic functions through a highly flexible macrocell and I/O structure. The architecture of the device supports both combinatorial-register and register-combinatorial-register forms of logic to easily accommodate state machine designs.

Figure 2 shows a global view of the 5AC324 architecture. The 5AC324 contains a total of 24 I/O programmable macrocells, 10 programmable input structures, and two clock inputs that can be programmed to function either as combinatorial inputs or clock inputs for the input structures and macrocells.

Each of the ten programmable inputs can be individually configured as a latch, register or flow-through




Figure 2. 5AC324 Global Architecture




Figure 3. 5AC324 Macrocell Architecture

input. Input latches/registers can be synchronously or asynchronously clocked.

Figure 3 shows the basic architecture of each of the 24 macrocells in the 5AC324. Each macrocell contains 16 p-terms (product terms), with 8 p-terms available for the global array and 8 p-terms dedicated to the four control signals: OE, PRESET, CLEAR, and ASYNCH. CLK. The 8 p-terms from the logic array are organized as a user-programmable AND array and a user-configurable OR array. The inputs to the AND array originate from the true and complement signals from the programmable input structure, the dedicated inputs, and the 48 feedback paths from the 24 I/O macrocells to the global bus. This global bus simplifies designing with the device by eliminating the need to partition a circuit to fit into a local/global internal bus structure.

INPUTS

Figure 4 shows a block diagram of the 5AC324 input structure. The device contains 10 user-programmable inputs that can be individually configured to operate in one of five modes:

- input register (D-register), synchronously clocked
- input register (D-register), asynchronously clocked
- input latch, (D-latch), synchronously clocked
- input latch, (D-latch), asynchronously clocked
- Flow-through input

Configuration is accomplished through the programming of EPROM architecture control bits via the logic compiler and programmer software. If synchronous operation is selected, the ILE/ICLK pin is used as a global latch/clock to all input latch/register

structures. For asynchronous operation, a separate product term in the array is used to derive the ILE/ICLK signal for each input structure. Because the clock signal for each programmable input can be individually selected, a mix between synchronously and asynchronously clocked inputs is possible. Software can configure each input structure as a flow-through input by selecting a latch and tying the ILE p-term to VCC. Data is latched/clocked on the falling edge of ILE/ICLK (synchronous mode). ILE/ICLK can function as an input to the logic array at the same time as it is used to synchronously clock the input registers.

MACROCELLS

Each of the 24 macrocells in the device contains 8 p-terms to support logic functions and 8 p-terms for control signals. The 8 p-terms for logic functions are subdivided into 2 groups, each with 4 p-terms. This grouping of p-terms supports the proprietary p-term allocation scheme in the 5AC324. Each macrocell also provides dual feedbacks to the logic array, which results in more efficient macrocell/pin usage than possible with single feedbacks.

Register Configuration

Each macrocell can be configured as a D, T, RS, or JK register. The 8 p-terms for control functions are organized so that 2 p-terms support each of the 4 control signals: Output Enable (OE), asynchronous I/O preset (PRESET), asynchronous I/O reset (CLEAR), and asynchronous I/O register clock (ASYNCH. CLK). Availability of 2 p-terms per control signal is another feature that increases the efficiency of the device by reducing the need to use intermediate macrocells sometimes needed to implement control functions.




Figure 4. 5AC324 Programmable Input Structure

CLK is a global clock signal that can be used to synchronously clock any or all macrocell registers. When CLK is not used as a synchronous clock, it functions only as a dedicated input to the logic array. CLK can be used as an input to the logic array at the same time as it is used as a macrocell clock.

Combinatorial Configuration

The macrocell register can be bypassed to implement combinatorial logic functions. When configured to provide combinatorial logic, only the OE control signal is used.

Invert Select Bit

An invert select EPROM bit is used to invert the product term input into each macrocell register, including double inputs on JK and SR registers. This invert option allows the highest possible logic utilization by use of DeMorgan's logic inversion.

LOGIC ARRAY

Each intersecting point in the logic array contains a programmable EPROM connection. Initially (erased state), all connections are complete, i.e., both true and complement states of all signals are connected to each p-term.

Connections are opened during programming. When both the true and complement connections exist, a logical false results on the output of the AND gate. If both the true and complement connections of a signal are programmed "open", then a logic "don't care" results for that signal. If all connections for a p-term are programmed open, then a logical true results on the output of the AND gate.

PRODUCT TERM ALLOCATION

Product Term (p-term) allocation is defined as taking logic resources (p-terms) from macrocells where they are not used to support demand for additional p-terms in other macrocells. In the 5AC324, p-term allocation can occur in increments of 4 p-terms between adjacent macrocells. The 5AC324 includes 2 rings of 12 macrocells each. P-term groups from one macrocell can be allocated to the adjacent macrocell in the ring. P-term allocation between the two rings is not supported.

EXAMPLE:

Figure 5 shows a p-term allocation example. In this example, the logic function in macrocell 4 requires 16 p-terms. In this case, software allocates 4 p-terms from the previous macrocell in Ring 1 (macrocell 5) and 4 p-terms from the next macrocell (macrocell 3) to accumulate a total of 16 p-terms ($8 + 4 + 4$). This implementation leaves macrocells 3 and 5 with a remainder of 4 p-terms. These remaining p-terms can also be allocated away to, or supplemented with p-terms from, their adjacent macrocells in Ring 1 (macrocells 2 and 6).

With this scheme, any macrocell inside the device can support logic functions requiring between 0 and 16 p-terms. P-terms allocated away do not affect that macrocell's output structure. The input to the macrocell can be tied to VCC or GND, even when all p-terms have been allocated away. Thus the register and all control signals are still available for use if needed.

Figure 6 shows adjacent macrocells in the 5AC324. Table 1 shows the previous and next macrocells for each macrocell in the device, along with the corresponding allocation ring. P-term allocation is implemented automatically in the development software and is transparent to the user. Users can still use explicit pin assignment, but should assign pins in a way that does not conflict with p-term allocation.

Software support allows the control signals on macrocells to be used to implement simple logic functions even when all the input p-terms have been allocated to adjacent macrocells.

DUAL-FEEDBACK/BURIED LOGIC

Macrocell output can be fed back to the logic array on either one of the two feedback paths. If the pin feedback is used (connected after the output buffer), bidirectional I/O can be implemented. If the internal feedback path is used to implement a buried register or buried logic function, the pin feedback is still available for use as an input. The availability of dual feedbacks on the 5AC324 enhances resource efficiency over single feedback devices.

AUTOMATIC STAND-BY MODE

The 5AC324 contains a programmable bit, the Turbo Bit, that optimizes operation for speed or for power savings. When the Turbo Bit is programmed (TURBO = ON), the device is optimized for maximum




Figure 5. P-Term Allocation Example (8 + 4 + 4)




Figure 6. 5AC324 Adjacent Macrocell

Table 1. Product Term Allocation Rings

RING 1			RING 2		
Current Macrocell	Next Macrocell	Previous Macrocell	Current Macrocell	Next Macrocell	Previous Macrocell
1	7	2	13	19	14
2	1	3	14	13	15
3	2	4	15	14	16
4	3	5	16	15	17
5	4	6	17	16	18
6	5	12	18	17	24
7	8	1	19	20	13
8	9	7	20	21	19
9	10	8	21	22	20
10	11	9	22	23	21
11	12	10	23	24	22
12	6	11	24	18	23

speed. When the Turbo Bit is not programmed (TURBO = OFF), the device is optimized for power savings by entering standby mode during periods of inactivity.

Figure 7 shows the device entering standby mode approximately 100 ns after the last input transition. When the next input transition is detected, the device returns to active mode. Wakeup time adds an additional 20 ns to the propagation delay through the device as measured from the first input. No delay will occur if an output is dependent on more than one input and the last of the inputs changes after the device has returned to active mode.

After erasure, the Turbo Bit is unprogrammed (OFF); automatic standby mode is enabled. When the Turbo Bit is programmed (ON), the device never enters standby mode.

POWER-ON CHARACTERISTICS

On V_{CC} power-up, the 5AC324 registers are reset to a logic low. Input latch/register output (to the logic array) are also set to a logic low. 5AC324 inputs and outputs begin responding approximately 20 μ s after V_{CC} power-up or after a power-loss/power-up sequence. After power-up, macrocells can be preset to a logic high via the PRESET control signal for each macrocell.

ERASED STATE CONFIGURATION

After erasure and prior to programming, all macrocells are configured as combinatorial outputs with output buffers three-stated. Inputs are configured as synchronous registers.




Figure 7. 5AC324 Standby and Active Mode Transitions

ERASURE CHARACTERISTICS

Erasure time for the 5AC324 is 1 hour at 12,000 $\mu\text{W}/\text{cm}^2$ with a 2537Å UV lamp.

Erasure characteristics of the device are such that erasure begins to occur upon exposure to light with wavelengths shorter than approximately 4000Å. It should be noted that sunlight and certain types of fluorescent lamps have wavelengths in the 3000Å-4000Å range. Data shows that constant exposure to room level fluorescent lighting could erase the typical 5AC324 in approximately six years, while it would take approximately two weeks to erase the device when exposed to direct sunlight. If the device is to be exposed to these lighting conditions for extended periods of time, conductive opaque labels should be placed over the device window to prevent unintentional erasure.

The recommended erasure procedure for the 5AC324 is exposure to shortwave ultraviolet light with a wavelength of 2537Å. The integrated dose (i.e., UV intensity x exposure time) for erasure should be a minimum of forty (40) Wsec/cm². The erasure time with this dosage is approximately 1 hour using an ultraviolet lamp with a 12,000 $\mu\text{W}/\text{cm}^2$ power rating. The device should be placed within 1 inch of the lamp tubes during exposure. The maximum integrated dose the 5AC324 can be exposed to without damage is 7258 Wsec/cm² (1 week at 12,000 $\mu\text{W}/\text{cm}^2). Exposure to high intensity UV light for longer periods may cause permanent damage to the device.$

intelligent Programming™ Algorithm

The 5AC324 supports the intelligent Programming Algorithm, which rapidly programs Intel EPLDs, and many of Intel's microcontrollers and EPROMs while maintaining a high degree of reliability. It is particularly suited for production programming environments. This method decreases the overall programming time while programming reliability is ensured as the incremental programming margin of each bit has been verified during programming. Programming voltage and waveform specifications are available by request from Intel to support programming the device.

DESIGN SECURITY

A Security Bit provides a programmable security option to protect the data programmed in the device. Once this bit is set during programming, subsequent

attempts to read the device architecture information are prevented. This method provides a higher degree of design security than fused-based devices, since programmed EPROM cells are invisible even to microscopic examination. The Security Bit (also called the Verify Protect Bit), along with all the other EPROM cells, is reset by erasing the device.

LATCH-UP IMMUNITY

All of the input, I/O, and clock pins of the device have been designed to resist latch-up which is inherent in inferior CMOS structures. The 5AC324 is designed with Intel's proprietary 1-micron CHMOS EPROM process. Thus, each of the pins will not experience latch-up with currents up to 100 mA and voltages ranging from -0.5V to ($V_{CC} + 0.5V$). The programming pin is designed to resist latch-up to the 13.5V maximum device limit.

DESIGN RECOMMENDATIONS

For proper operation, it is recommended that all input and output pins be constrained to the voltage range $GND \leq (V_{IN} \text{ or } V_{OUT}) \leq V_{CC}$. All unused inputs and I/Os should be tied high or low to minimize power consumption (do not leave them floating). A power supply decoupling capacitor of at least 0.2 μF must be connected directly between each V_{CC} and GND pin.

As with all CMOS devices, ESD handling procedures should be used with the 5AC324 to prevent damage to the device during programming, assembly, and test.

FUNCTIONAL TESTING

Since the logical operation of the 5AC324 is controlled by EPROM elements, the device is completely testable during the manufacturing process. Each programmable EPROM bit controlling the internal logic is tested using application independent test patterns. EPROM cells in the device are 100% tested for programming and erasure. After testing, the devices are erased before shipments to the customers. No post-programming tests of the EPROM array are required.

The testability and reliability of EPROM-based programmable logic devices is an important feature over similar devices based on fuse technology. Fuse-based programmable logic devices require a user to perform post-programming tests to insure

device functionality. During the manufacturing process, tests on fuse-based parts can only be performed in very restricted ways in order to avoid pre-programming the array.

ADF PRIMITIVES SUPPORTED

The following ADF primitives are supported by this device:

INP	NOTF
LINP	JOJF
RINP	JONF
CONF	SONF
COCF	SOSF
COIF	TOIF
RONF	TONF
ROIF	TOTF
RORF	CLKB
NOCF	LINB
NORF	
NOJF	
NOSF	

DESIGN SOFTWARE

Full logic compilation and programming support is provided by Version 2.0 (or later) of iPLS II. The GUPI 40D44J provides programming support for the device.

iPLS II software interfaces to several schematic capture packages to enable designs to be entered in schematic form. IPLDview-286/IPLDdraw allows the designer to use familiar TTL symbols or EPLD design primitive symbols. User-defined symbols are also supported. These products also provide a path to A.C. timing simulation of EPLD designs.

SCHEMA II-PLD allows the designer to use TTL symbols, EPLD custom macros, or EPLD design primitive symbols. It also supports user-defined symbols.

Other design formats include Boolean equation entry (supported directly by iPLS II) and state machine entry (supported by iSTATE).

Refer to the iPLDS II (Intel Programmable Logic Development System II) Data Sheet (Order Number: 280168) for details on the software. Refer to the tools section of the *Programmable Logic* handbook for a complete listing of development tools.

ORDERING INFORMATION

t _{PD} (ns)	t _{CO} (ns)	f _{MAX} (MHz)	Order Code	Package	Operating Range
25	17.8	66	N5AC324-25	PLCC	Commercial
			P5AC324-25	PDIP	
			D5AC324-25	*CERDIP	
30	20	50	N5AC324-30	PLCC	Commercial
			P5AC324-30	PDIP	
			D5AC324-30	*CERDIP	
35	22	40	N5AC324-35	PLCC	Commercial
			P5AC324-35	PDIP	
			D5AC324-35	*CERDIP	

*Windowed package allows UV erase.

ABSOLUTE MAXIMUM RATINGS*

Supply Voltage (V_{CC})⁽¹⁾ -2.0V to +7.0V
 Programming Supply
 Voltage (V_{PP})⁽¹⁾ -2.0V to +13.5V
 D.C. Input Voltage (V_I)^(1,2) -0.5V to $V_{CC} + 0.5V$
 Storage Temperature (T_{stg}) -65°C to +150°C
 Ambient Temperature (T_{amb})⁽³⁾ -10°C to +85°C

NOTES:

1. Voltage with respect to GND.
2. Minimum D.C. input is -0.5V. During transitions, the inputs may undershoot to -2.0V or overshoot to +7.0V less than 20 ns under no load conditions.
3. Under bias. Extended Temperature versions are also available.

**Notice: Stresses above those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.*

NOTICE: Specifications contained within the following tables are subject to change.

RECOMMENDED OPERATING CONDITIONS

Symbol	Parameter	Min	Max	Unit
V_{CC}	Supply Voltage	4.75	5.25	V
V_{IN}	Input Voltage	0	V_{CC}	V
V_O	Output Voltage	0	V_{CC}	V
T_A	Operating Temperature	0	+70	°C
t_R	Input Rise Time		500	ns
t_F	Input Fall Time		500	ns


D.C. CHARACTERISTICS ($T_A = 0^\circ\text{C}$ to $+70^\circ\text{C}$, $V_{CC} = 5.0V \pm 5\%$)

Symbol	Parameter	Min	Typ	Max	Unit	Test Conditions
$V_{IH}^{(4)}$	High Level Input Voltage	2.0		$V_{CC} + 0.3$	V	
$V_{IL}^{(4)}$	Low Level Input Voltage	-0.3		0.8		
$V_{OH}^{(5)}$	High Level Output Voltage	2.4			V	$I_O = -4.0$ mA D.C., $V_{CC} = \text{min.}$
V_{OL}	Low Level Output Voltage			0.45	V	$I_O = 8.0$ mA D.C., $V_{CC} = \text{min.}$
I_I	Input Leakage Current			± 10	μA	$V_{CC} = \text{max.}$, $\text{GND} < V_{IN} < V_{CC}$
I_{OZ}	Output Leakage Current			± 10	μA	$V_{CC} = \text{max.}$, $\text{GND} < V_{OUT} < V_{CC}$
$I_{SC}^{(6)}$	Output Short Circuit Current	-30		-90	mA	$V_{CC} = \text{max.}$, $V_{OUT} = 0.5V$
$I_{SB}^{(7)}$	Standby Current		150	300	μA	$V_{CC} = \text{max.}$, $V_{IN} = V_{CC}$ or GND, Standby Mode
I_{CC}	Power Supply Current		20		mA	$V_{CC} = \text{max.}$, $V_{IN} = V_{CC}$ or GND, No Load, $f_{IN} = 1$ MHz, Active Mode (Turbo Off), Device Prog. as Two 12-Bit Counters


NOTES:

4. Absolute values with respect to device GND; all over and undershoots due to system or tester noise are included.
5. I_O at CMOS levels (3.84V) = -2 mA.
6. Not more than 1 output should be tested at a time. Duration of that test should not exceed 1 second.
7. With Turbo Bit Off, device automatically enters standby mode approximately 100 ns after last input transition.

A.C. TESTING LOAD CIRCUIT



A.C. TESTING INPUT, OUTPUT WAVEFORM



CAPACITANCE

Symbol	Parameter	Min	Typ	Max	Unit	Conditions
C_{IN}	Input Capacitance			8	pF	$V_{IN} = 0V, f = 1.0 \text{ MHz}$
C_{OUT}	I/O Capacitance			15	pF	$V_{OUT} = 0V, f = 1.0 \text{ MHz}$
C_{CLK}	Clock Pin Capacitance			15	pF	$V_{IN} = 0V, f = 1.0 \text{ MHz}$
C_{VPP}	V_{PP} Pin (LIN3)			25	pF	$V_{IN} = 0V, f = 1.0 \text{ MHz}$

COMBINATORIAL MODE A.C. CHARACTERISTICS(T_A = 0°C to +70°C, V_{CC} = 5.0V ±5%, Turbo Bit On)⁽⁸⁾

Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
t _{PD}	Input or I/O to Output		20	25		25	30		30	35	+ 20	ns
t _{PZX} ⁽¹⁰⁾	Input or I/O to Output Enable		20	25		25	30		30	35	+ 20	ns
t _{PXZ} ⁽¹⁰⁾	Input or I/O to Output Disable		20	25		25	30		30	35	+ 20	ns
t _{CLR}	Asynch. Reset to Q Clear		20	25		25	30		30	35	+ 20	ns
t _{SET}	Asynch. Set to Q Set		20	25		25	30		30	35	+ 20	ns

NOTES:8. Typical values are at T_A = +25°C, V_{CC} = 5V, Active Mode.

9. If device is operated with Turbo bit Off (Non-Turbo Mode) and the device is inactive for approx. 100 ns, increase time by amount shown.

10. t_{PZX} and t_{PXZ} measured at ±0.5V from steady-state voltage as driven by spec. output load. t_{PXZ} measured with C_L = 5 pF.**SYNCHRONOUS CLOCK MODE (MACROCELLS) A.C. CHARACTERISTICS**(T_A = 0°C to +70°C, V_{CC} = 5.0V ±5%, Turbo Bit On)⁽⁸⁾

Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
f _{MAX}	Maximum Frequency (Pipelined) (1/t _{CW})—No Feedback		80	66		60	50		50	40		MHz
f _{CNT1}	Maximum Frequency (1/t _{SU} + t _{CO}) —External Feedback		40	33		33.3	25		27	21.2		MHz
f _{CNT2}	Maximum Frequency (1/t _{CNT}) —Internal Feedback		40	33		33.3	28.5		28.5	25		MHz
t _{SU1}	Input Setup Time to CLK ↑	12.5	10		20	15		25	20		+ 20	ns
t _{SU2}	I/O Setup Time to CLK ↑	12	10		20	15		25	20		+ 20	ns
t _H	Input or I/O Hold Time from CLK ↑	0			0			0				ns
t _{CO}	CLK ↑ to Output Valid		15	17.8		15	20		17	22		ns
t _{CNT}	Register Output Feedback to Register Input— Internal Path	30			35	30		40	35		+ 20	ns
t _{CH}	Clock High Time	7.5			10			12.5				ns
t _{CL}	Clock Low Time	7.5			10			12.5				ns
t _{CW}	Minimum Clock Period	15			20			25				ns

SYNCHRONOUS CLOCK MODE (INPUT STRUCTURE) A.C. CHARACTERISTICS

(T_A = 0°C to +70°C, V_{CC} = 5.0V ±5%, Turbo Bit On)⁽⁸⁾

Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
f _{MAXI}	Maximum Frequency (1/t _{CWI})		80	66		60	50		50	40		MHz
t _{SUIR}	Input Register Setup Time Before ICLK ↓	1			2.5			5				ns
t _{ESUI}	Input Latch Setup Time Before ILE ↑	1			2.5			5				ns
t _{COI}	ICLK ↓ to Comb. Output	25	30			30	35		35	40	+ 20	ns
t _{EOI}	ILE ↑ to Comb. Output	25	30			30	35		35	40	+ 20	ns
t _{HI}	Input Hold after ICLK ↓	8			9			10				ns
t _{EHI}	Input Hold after ILE ↓	7			8			9				ns
t _{CHI}	ILE/ICLK High Time	7.5			10			12.5				ns
t _{CLI}	ILE/ICLK Low Time	7.5			10			12.5				ns
t _{CWI}	Minimum Input Clock Period	15			20			25				ns

ASYNCHRONOUS CLOCK MODE (MACROCELLS) A.C. CHARACTERISTICS

(T_A = 0°C to +70°C, V_{CC} = 5.0V ±5%, Turbo Bit On)⁽⁸⁾

Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
f _{AMAX}	Max. Frequency (Pipelined) (1/t _{ACW})—No Feedback		80	66		60	50		50	40		MHz
f _{ACNT1}	Max. Frequency (1/t _{ASU} + t _{ACO}) External Feedback		32.2	27.7		27	23.8		22.2	20		MHz
f _{ACNT2}	Max. Frequency (1/t _{ACNT}) Internal Feedback		40	33.3		33.3	28.5		28.5	25		MHz
t _{ASU1}	Input Setup Time to Asynch. CLK	11			12			15			+ 20	ns
t _{ASU2}	I/O Setup Time to Asynch. CLK	11			12			15			+ 20	ns
t _{AH}	Input or I/O Hold Time from Asynch. CLK	3	0		4	0		5	0			ns
t _{ACO}	Asynch. CLK to Output Valid		20	25		25	30		30	35	+ 20	ns
t _{ACNT}	Asynch. Output Feedback to Register Input - Internal Path	30	25		35	30		40	35		+ 20	ns
t _{ACH}	Asynch. CLK High Time	7.5			10			12.5			+ 20	ns
t _{ACL}	Asynch. CLK Low Time	7.5			10			12.5			+ 20	ns
t _{ACW}	Asynch. CLK Period	15			20			25			+ 20	ns

ASYNCHRONOUS CLOCK MODE (INPUT STRUCTURE) A.C. CHARACTERISTICS

 $(T_A = 0^{\circ}\text{C to } +70^{\circ}\text{C}, V_{CC} = 5.0\text{V} \pm 5\%, \text{ Turbo Bit On})^{(8)}$

Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
f_{AMAXI}	Maximum Frequency Input Register ($1/t_{ACWI}$)		80	66		60	50		50	40		MHz
t_{ASUIR}	Input Register Setup Time Before Asynch. ICLK	-5			-5			-5				ns
t_{AESUI}	Input Latch Setup Time Before Asynch. ILE	-5			-5			-5				ns
t_{ACOI}	Asynch. ICLK to Comb. Output		35	40		40	45		45	50	+ 20	ns
t_{AEOI}	Asynch. ILE to Comb. Output		35	40		40	5		45	50	+ 20	ns
t_{AHI}	Input Hold after Asynch. ICLK	15			18			20				ns
t_{AEHI}	Input Hold after Asynch. ILE	16			17			19				ns
t_{ACHI}	Asynch. ILE/ICLK High Time	7.5			10			12.5			+ 20	ns
t_{ACLI}	Asynch. ILE/ICLK Low Time	7.5			10			12.5			+ 20	ns
t_{ACWI}	Minimum Input Clock Period	15			20			25			+ 20	ns

INPUT-CLOCK-TO-MACROCELL-CLOCK A.C. CHARACTERISTICS

 $(T_A = 0^{\circ}\text{C to } +70^{\circ}\text{C}, V_{CC} = 5.0\text{V} \pm 5\%, \text{ Turbo Bit On})^{(8)}$


Symbol	Parameter	5AC324-25			5AC324-30			5AC324-35			Non-Turbo ⁽⁹⁾ Mode	Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max		
$t_{C1C2}^{(11)}$	Synchronous ILE/ICLK to Synchronous Macrocell CLK	20			25			30			+ 20	ns
	Synchronous ILE/ICLK to Asynchronous Macrocell CLK	12.5			15			18			+ 20	ns
	Asynchronous ILE/ICLK to Synchronous Macrocell CLK	40			45			50			+ 20	ns
	Asynchronous ILE/CLK to Asynchronous Macrocell CLK	20			25			30			+ 20	ns

NOTE:


11. Times for SETUP, HOLD, and OUTPUT VALID are shown in previous tables.

SWITCHING WAVEFORMS


COMBINATORIAL MODE




SYNCHRONOUS CLOCK MODE (MACROCELLS)




SYNCHRONOUS CLOCK MODE (INPUT STRUCTURE)




ASYNCHRONOUS CLOCK MODE (MACROCELLS)




ASYNCHRONOUS CLOCK MODE (INPUT STRUCTURE)




INPUT-CLOCK-TO-MACROCELL CLOCK TIMING (CLOCKED PIPELINED DATA)



5AC324 I_{CC} vs. Frequency



5AC324 t_{PD} Derating vs. Capacitive Loading





DOMESTIC SALES OFFICES

ALABAMA

Intel Corp.
5015 Bradford Dr., #2
Huntsville 35805
Tel: (205) 830-4010
FAX: (205) 837-2640

ARIZONA

Intel Corp.
11225 N. 28th Dr.
Suite D-214
Phoenix 85029
Tel: (602) 969-4980
FAX: (602) 869-4294

Intel Corp.
1161 N. El Dorado Place
Suite 301
Tucson 85715
Tel: (602) 299-6815
FAX: (602) 296-8234

CALIFORNIA

Intel Corp.
21515 Vanowen Street
Suite 116
Canoga Park 91303
Tel: (818) 704-8500
FAX: (818) 340-1144

Intel Corp.
2250 E. Imperial Highway
Suite 218
El Segundo 90245
Tel: (213) 640-6040
FAX: (213) 640-7133

Intel Corp.
1510 Arden Way
Suite 101
Sacramento 95815
Tel: (916) 920-8096
FAX: (916) 920-8253

Intel Corp.
9665 Chesapeake Dr.
Suite 325
San Diego 95123
Tel: (619) 292-8086
FAX: (619) 292-0628

Intel Corp.*
400 N. Tustin Avenue
Suite 450
Santa Ana 92705
Tel: (714) 835-9642
TWX: 910-595-1114
FAX: (714) 541-9157

Intel Corp.*
San Tomas 4
2700 San Tomas Expressway
2nd Floor
Santa Clara 95051
Tel: (408) 986-8086
TWX: 910-338-0255
FAX: (408) 727-2620

COLORADO

Intel Corp.
4445 Northpark Drive
Suite 100
Colorado Springs 80907
Tel: (719) 594-6622
FAX: (303) 594-0720

Intel Corp.*
650 S. Cherry St.
Suite 915
Denver 80222
Tel: (303) 321-8086
TWX: 910-931-2289
FAX: (303) 322-8670

CONNECTICUT

Intel Corp.
301 Lee Farm Corporate Park
83 Wooster Heights Rd.
Danbury 06810
Tel: (203) 748-3130
FAX: (203) 734-0339

FLORIDA

Intel Corp.
6363 N.W. 8th Way
Suite 100
FL Lauderdale 33309
Tel: (305) 771-0600
TWX: 510-958-9407
FAX: (305) 772-6193

Intel Corp.
5850 T.G. Lee Blvd.
Suite 340
Orlando 32822
Tel: (407) 240-8000
FAX: (407) 240-8097

Intel Corp.
11300 4th Street North
Suite 170
St. Petersburg 33716
Tel: (813) 577-2413
FAX: (813) 578-1607

GEORGIA

Intel Corp.
20 Technology Parkway, N.W.
Suite 150
Norcross 30092
Tel: (404) 449-0541
FAX: (404) 605-9762

ILLINOIS

Intel Corp.*
300 N. Martingale Road
Suite 400
Schaumburg 60173
Tel: (312) 605-8031
FAX: (312) 706-9762

INDIANA

Intel Corp.
8777 Purdue Road
Suite 125
Indianapolis 46268
Tel: (317) 875-0623
FAX: (317) 875-8938

IOWA

Intel Corp.
1930 St. Andrews Drive N.E.
2nd Floor
Cedar Rapids 52402
Tel: (319) 393-1294

KANSAS

Intel Corp.
10985 Cody St.
Suite 140, Bldg. D
Overland Park 66210
Tel: (913) 345-2727
FAX: (913) 345-2076

MARYLAND

Intel Corp.*
10010 Ford Road
Suite 200
Annapolis Junction 20701
Tel: (301) 206-2860
FAX: (301) 206-3677
(301) 206-3678

MASSACHUSETTS

Intel Corp.*
Westford Corp. Center
3 Carlisle Road
2nd Floor
Westford 01886
Tel: (508) 692-3222
TWX: 710-343-6333
FAX: (508) 692-7867

MICHIGAN

Intel Corp.
7071 Orchard Lake Road
Suite 100
West Bloomfield 48322
Tel: (313) 851-8096
FAX: (313) 851-8770

MINNESOTA

Intel Corp.
3500 W. 80th St.
Suite 360
Bloomington 55431
Tel: (612) 835-6722
TWX: 910-576-2867
FAX: (612) 831-6497

MISSOURI

Intel Corp.
4035 Earth City Expressway
Suite 131
Earth City 63045
Tel: (314) 291-1990
FAX: (314) 291-4341

NEW JERSEY

Intel Corp.*
Parkway 109 Office Center
328 Newman Springs Road
Red Bank 07701
Tel: (201) 747-2233
FAX: (201) 747-0983

Intel Corp.
280 Corporate Center
75 Livingston Avenue
First Floor
Roseland 07068
Tel: (201) 740-0111
FAX: (201) 740-0626

NEW YORK

Intel Corp.*
850 Cross Keys Office Park
Fairport 14450
Tel: (716) 425-2750
TWX: 510-253-7391
FAX: (716) 223-2581

Intel Corp.*
2950 Expressway Dr., South
Suite 130
Islandia 11722
Tel: (516) 231-3300
TWX: 510-227-6236
FAX: (516) 348-7939

Intel Corp.
Westgate Business Center
Bldg. 300, Route 9
Fishkill 12524
Tel: (914) 897-3860
FAX: (914) 897-3125

NORTH CAROLINA

Intel Corp.
5800 Executive Center Dr.
Suite 105
Charlotte 28212
Tel: (704) 569-8866
FAX: (704) 535-2236

Intel Corp.
5540 Centerview Dr.
Suite 215
Raleigh 27606
Tel: (919) 851-9537
FAX: (919) 851-8974

OHIO

Intel Corp.*
3401 Park Center Drive
Suite 220
Dayton 45414
Tel: (513) 890-5350
TWX: 810-450-2528
FAX: (513) 890-8658

Intel Corp.*
25700 Science Park Dr.
Suite 100
Beachwood 44122
Tel: (216) 464-2736
TWX: 810-427-9298
FAX: (804) 282-0673

OKLAHOMA

Intel Corp.
6801 N. Broadway
Suite 115
Oklahoma City 73162
Tel: (405) 848-8086
FAX: (405) 840-9819

OREGON

Intel Corp.
15254 N.W. Greenbrier Parkway
Building B
Beaverton 97005
Tel: (503) 645-8051
TWX: 910-467-8741
FAX: (503) 645-8181

PENNSYLVANIA

Intel Corp.*
455 Pennsylvania Avenue
Suite 230
Fort Washington 19034
Tel: (215) 641-1000
TWX: 510-661-2077
FAX: (215) 641-0785

Intel Corp.*
400 Penn Center Blvd.
Suite 610
Pittsburgh 15235
Tel: (412) 823-4970
FAX: (412) 829-7578

PUERTO RICO

Intel Corp.
South Industrial Park
P.O. Box 910
Las Piedras 00671
Tel: (809) 733-8616

TEXAS

Intel Corp.
8911 Capital of Texas Hwy.
Austin 78759
Tel: (512) 794-8086
FAX: (512) 338-9335

Intel Corp.*
12000 Ford Road
Suite 400
Dallas 75204
Tel: (214) 241-8087
FAX: (214) 484-1180

Intel Corp.*
7322 S.W. Freeway
Suite 1490
Houston 77074
Tel: (713) 988-8086
TWX: 910-881-2490
FAX: (713) 988-3660

UTAH

Intel Corp.
428 East 8400 South
Suite 104
Murray 84107
Tel: (801) 453-8051
TWX: (801) 268-1457
FAX: (801) 268-1457

VIRGINIA

Intel Corp.
1504 Santa Rosa Road
Suite 108
Richmond 23288
Tel: (804) 282-5668
FAX: (216) 464-2270

WASHINGTON

Intel Corp.
155 108th Avenue N.E.
Suite 386
Bellevue 98004
Tel: (206) 453-8086
FAX: (206) 453-3002
FAX: (206) 451-5556

Intel Corp.
408 N. Mullian Road
Suite 102
Spokane 99206
Tel: (509) 928-8086
FAX: (509) 928-9467

WISCONSIN

Intel Corp.
330 S. Executive Dr.
Suite 102
Brookfield 53005
Tel: (414) 784-8087
FAX: (414) 796-2115

CANADA

BRITISH COLUMBIA

Intel Semiconductor of
Canada, Ltd.
4585 Canada Way
Suite 202
Burnaby V5G 4L6
Tel: (604) 296-0387
FAX: (604) 298-8234

ONTARIO

Intel Semiconductor of
Canada, Ltd.
2650 Queensview Drive
Suite 250
Ottawa K2B 8H6
Tel: (613) 829-9714
FAX: (613) 820-5936

Intel Semiconductor of
Canada, Ltd.
190 Attwell Drive
Suite 500
Rexdale M9W 6H8
Tel: (416) 675-2105
FAX: (416) 675-2438

QUEBEC

Intel Semiconductor of
Canada, Ltd.
620 St. Jean Boulevard
Pointe Claire H9R 3K2
Tel: (514) 694-9130
FAX: 514-694-0064



DOMESTIC DISTRIBUTORS

ALABAMA

Arrow Electronics, Inc.
1105 Henderson Road
Huntsville 35895
Tel: (205) 837-6955

Hamilton/Avnet Electronics
4940 Research Drive
Huntsville 35805
Tel: (205) 837-7210
TWX: 810-726-2162

Pioneer/Technologies Group, Inc.
4825 University Square
Huntsville 35895
Tel: (205) 837-9300
TWX: 810-726-2197

ARIZONA

Hamilton/Avnet Electronics
505 S. Madison Drive
Tempe 85281
Tel: (602) 231-5140
TWX: 910-950-0077

Hamilton/Avnet Electronics
30 South McKelmy
Chandler 85226
Tel: (602) 961-6669
TWX: 910-950-0077

Arrow Electronics, Inc.
4134 E. Wood Street
Phoenix 85040
Tel: (602) 437-0750
TWX: 910-951-1550

Wyle Distribution Group
17855 N. Black Canyon Hwy.
Phoenix 85023
Tel: (602) 249-2232
TWX: 910-951-4282

CALIFORNIA

Arrow Electronics, Inc.
10824 Hope Street
Cypress 90630
Tel: (714) 220-6300

Arrow Electronics, Inc.
19749 Dearborn Street
Chatsworth 91311
Tel: (213) 701-7500
TWX: 910-493-2086

Arrow Electronics, Inc.
521 Weddell Drive
Sunnyvale 94086
Tel: (408) 745-6600
TWX: 910-339-9371

Arrow Electronics, Inc.
9511 Ridgehaven Court
San Diego 92123
Tel: (619) 565-4800
TWX: 888-064

Arrow Electronics, Inc.
2961 Dow Avenue
Tustin 92680
Tel: (714) 838-5422
TWX: 910-595-2860

Avnet Electronics
350 McCormick Avenue
Costa Mesa 92626
Tel: (714) 754-6071
TWX: 910-595-1928

Hamilton/Avnet Electronics
1175 Bordeaux Drive
Sunnyvale 94086
Tel: (408) 743-3300
TWX: 910-339-9332

Hamilton/Avnet Electronics
4545 Ridgeview Avenue
San Diego 92123
Tel: (619) 571-7500
TWX: 910-595-2638

Hamilton/Avnet Electronics
9650 Desoto Avenue
Chatsworth 91311
Tel: (818) 700-1161

Hamilton Electro Sales
10950 W. Washington Blvd.
Culver City 90230
Tel: (213) 558-2458
TWX: 910-340-6364

Hamilton Electro Sales
1361B West 190th Street
Gardena 90248
Tel: (213) 217-6700

Hamilton/Avnet Electronics
3002 'G' Street
Ontario 91761
Tel: (714) 989-9411

Avnet Electronics
20501 Plummer
Chatsworth 91351
Tel: (213) 700-6271
TWX: 910-494-2207

Hamilton Electro Sales
3170 Pullman Street
Costa Mesa 92626
Tel: (714) 641-4150
TWX: 910-595-2638

Hamilton/Avnet Electronics
4103 Northgate Blvd.
Sacramento 95834
Tel: (916) 920-3150

Wyle Distribution Group
124 Maryland Street
El Segundo 90254
Tel: (213) 922-6100

Wyle Distribution Group
7382 Lampson Ave.
Garden Grove 92641
Tel: (714) 891-1717
TWX: 910-348-7140 or 7111

Wyle Distribution Group
11151 Sun Center Drive
Rancho Cordova 95670
Tel: (916) 638-5282

Wyle Distribution Group
9525 Chesapeake Drive
San Diego 92123
Tel: (619) 565-9171
TWX: 910-335-1590

Wyle Distribution Group
3000 Bowers Avenue
Santa Clara 95051
Tel: (408) 727-2500
TWX: 910-338-0296

Wyle Distribution Group
17872 Cowan Avenue
Irving 92714
Tel: (714) 863-9953
TWX: 910-595-1572

Wyle Distribution Group
26677 W. Agoura Rd.
Calabasas 91302
Tel: (818) 880-9000
TWX: 372-0232

COLORADO

Arrow Electronics, Inc.
7060 South Tucson Way
Englewood 80112
Tel: (303) 790-4444

Hamilton/Avnet Electronics
8765 E. Orchard Road
Suite 708
Englewood 80111
Tel: (303) 740-1017
TWX: 910-935-0787

Wyle Distribution Group
451 E. 124th Avenue
Thornton 80241
Tel: (303) 457-9953
TWX: 910-936-0770

CONNECTICUT

Arrow Electronics, Inc.
12 Beaumont Road
Wallingford 06492
Tel: (203) 265-7741
TWX: 710-476-0162

Hamilton/Avnet Electronics
Commerce Industrial Park
Commerce Drive
Danbury 06810
Tel: (203) 797-2800
TWX: 710-456-9974

Pioneer Electronics
112 Main Street
Norwalk 06851
Tel: (203) 853-1515
TWX: 710-468-3373

FLORIDA

Arrow Electronics, Inc.
400 Fairway Drive
Suite 102
Deerfield Beach 33441
Tel: (305) 429-8200
TWX: 810-955-9456

Arrow Electronics, Inc.
37 Skyline Drive
Suite 3101
Lake Mary 32746
Tel: (407) 323-0252
TWX: 810-958-6537

Hamilton/Avnet Electronics
6801 N.W. 15th Way
Ft. Lauderdale 33309
Tel: (305) 971-2900
TWX: 510-956-3097

Hamilton/Avnet Electronics
3197 Tech Drive North
St. Petersburg 33702
Tel: (813) 576-3930
TWX: 810-863-0374

Hamilton/Avnet Electronics
6947 University Boulevard
Winter Park 32792
Tel: (405) 628-3888
TWX: 810-853-0322

Pioneer/Technologies Group, Inc.
337 S. Lake Blvd.
Alta Monte Springs 32701
Tel: (407) 834-9090
TWX: 810-853-0284

Pioneer/Technologies Group, Inc.
674 S. Military Trail
Deerfield Beach 33442
Tel: (305) 428-8877
TWX: 510-955-9653

GEORGIA

Arrow Electronics, Inc.
3155 Northwoods Parkway
Suite A
Norcross 30071
Tel: (404) 449-8252
TWX: 810-766-0439

Hamilton/Avnet Electronics
5825 D Peachtree Corners
Norcross 30092
Tel: (404) 447-7500
TWX: 810-766-0432

Pioneer/Technologies Group, Inc.
3100 F Northwoods Place
Norcross 30071
Tel: (404) 448-1711
TWX: 810-766-4515

ILLINOIS

Arrow Electronics, Inc.
1140 W. Thorndale
Itasca 60143
Tel: (312) 250-0500
TWX: 312-250-0916

Hamilton/Avnet Electronics
1130 Thorndale Avenue
 Bensenville 60106
Tel: (312) 860-7780
TWX: 910-227-0060

MTI Systems Sales
1100 W. Thorndale
Itasca 60143
Tel: (312) 773-2300

Pioneer Electronics
1551 Carmen Drive
Elk Grove Village 60007
Tel: (312) 437-9680
TWX: 910-222-1934

INDIANA

Arrow Electronics, Inc.
2495 Directors Row, Suite H
Indianapolis 46241
Tel: (317) 243-9353
TWX: 810-341-3119

Hamilton/Avnet Electronics
185 Grady Drive
Carmel 46032
Tel: (317) 844-9333
TWX: 810-260-3966

Pioneer Electronics
6408 Castleplace Drive
Indianapolis 46250
Tel: (317) 949-7300
TWX: 810-260-1794

IOWA

Hamilton/Avnet Electronics
915 33rd Avenue, S.W.
Cedar Rapids 52404
Tel: (319) 362-4757

KANSAS

Arrow Electronics
8208 Melrose Dr., Suite 210
Lenexa 66214
Tel: (913) 541-9542

Hamilton/Avnet Electronics
9219 Quivera Road
Overland Park 66215
Tel: (913) 888-8900
TWX: 910-743-0005

Pioneer/Tec Gr.
10551 Lockman Rd.
Lenexa 66215
Tel: (913) 492-0500

KENTUCKY

Hamilton/Avnet Electronics
1051 D. Newton Park
Lexington 40511
Tel: (606) 259-1475

MARYLAND

Arrow Electronics, Inc.
8300 Guilford Drive
Suite H, River Center
Columbia 21046
Tel: (301) 995-0003
TWX: 710-236-9005

Hamilton/Avnet Electronics
6822 Oak Hall Lane
Columbia 21045
Tel: (301) 995-3500
TWX: 710-862-1861

Mesa Technology Corp.
9720 Patuxent Woods Dr.
Columbia 21046
Tel: (301) 290-8150
TWX: 710-828-9702

Pioneer/Technologies Group, Inc.
9100 Galther Road
Gaithersburg 20877
Tel: (301) 921-0660
TWX: 710-828-0545

Arrow Electronics, Inc.
7524 Standish Place
Rockville 20855
Tel: 301-424-0244

MASSACHUSETTS

Arrow Electronics, Inc.
25 Upton Dr.
Wilmington 01887
Tel: (617) 935-5134

Hamilton/Avnet Electronics
100 Centennial Drive
Peabody 01960
Tel: (617) 531-7430
TWX: 910-393-0382

MTI Systems Sales
83 Cambridge St.
Burlington 01813

Pioneer Electronics
44 Hartwell Avenue
Lexington 02173
Tel: (617) 861-9000
TWX: 710-326-6617

MICHIGAN

Arrow Electronics, Inc.
755 Phoenix Drive
Ann Arbor 48104
Tel: (313) 971-8220
TWX: 810-223-6020

Hamilton/Avnet Electronics
2215 29th Street S.E.
Space A5
Grand Rapids 49508
Tel: (616) 243-8905
TWX: 810-274-6921

Pioneer Electronics
4504 Broadmoor S.E.
Grand Rapids 49508
Fax: 616-698-1631

Hamilton/Avnet Electronics
32487 Schoolcraft Road
Livonia 48150
Tel: (313) 522-4070
TWX: 810-282-9775

Pioneer/Michigan
13465 Stamford
Livonia 48150
Tel: (313) 525-1800
TWX: 810-242-3271

MINNESOTA

Arrow Electronics, Inc.
5230 W. 73rd Street
Edina 55435
Tel: (612) 830-1800
TWX: 910-576-3125

Hamilton/Avnet Electronics
12400 Whitewater Drive
Minnetonka 55434
Tel: (612) 932-0600

Pioneer Electronics
7625 Golden Triangle Dr.
Suite G
Eden Prairie 55343
Tel: (612) 944-3355

MISSOURI

Arrow Electronics, Inc.
2380 Schuetz
St. Louis 63141
Tel: (314) 567-6888
TWX: 910-764-0882

Hamilton/Avnet Electronics
13743 Shoreline Court
Earth City 63045
Tel: (314) 344-1200
TWX: 910-762-0684

NEW HAMPSHIRE

Arrow Electronics, Inc.
3 Perimeter Road
Manchester 03103
Tel: (603) 686-6968
TWX: 710-220-1584

Hamilton/Avnet Electronics
444 E. Industrial Drive
Manchester 03103
Tel: (603) 624-9400



DOMESTIC DISTRIBUTORS (Contd.)

NEW JERSEY

†Arrow Electronics, Inc.
Four East Slow Road
Unit 11
Marion 08053
Tel: (609) 596-8000
TWX: 710-897-0829

†Arrow Electronics
6 Century Drive
Parsippany 07054
Tel: (201) 536-0900

†Hamilton/Avnet Electronics
1 Keystone Ave., Bldg. 36
Cherry Hill 08003
Tel: (609) 424-0110
TWX: 710-940-0262

†Hamilton/Avnet Electronics
10 Industrial
Fairfield 07006
Tel: (201) 575-5300
TWX: 710-734-4388

†MTI Systems Sales
37 Kulick Rd.
Fairfield 07006
Tel: (201) 227-5552

†Pioneer Electronics
45 Route 46
Pinetbrook 07058
Tel: (201) 575-3510
TWX: 710-734-4382

NEW MEXICO

Alliance Electronics Inc.
11030 Cochiti S.E.
Albuquerque 87123
Tel: (505) 292-3360
TWX: 910-989-1151

Hamilton/Avnet Electronics
2524 Baylor Drive S.E.
Albuquerque 87106
Tel: (505) 765-1500
TWX: 910-989-0614

NEW YORK

†Arrow Electronics, Inc.
3375 Brighton Henrietta
Towline Rd.
Rochester 14623
Tel: (716) 275-0300
TWX: 510-253-4766

Arrow Electronics, Inc.
20 Oser Avenue
Hauppauge 11788
Tel: (516) 231-1000
TWX: 510-227-6623

Hamilton/Avnet
933 Motor Parkway
Hauppauge 11788
Tel: (516) 231-0800
TWX: 510-224-6166

†Hamilton/Avnet Electronics
533 Meiro Park
Rochester 14623
Tel: (716) 475-9130
TWX: 510-253-5470

†Hamilton/Avnet Electronics
103 Twin Oaks Drive
Syracuse 13206
Tel: (315) 437-0288
TWX: 710-541-1560

†MTI Systems Sales
58 Harbor Park Drive
Port Washington 11050
Tel: (516) 621-6200

†Pioneer Electronics
68 Corporate Drive
Binghamton 13904
Tel: (607) 722-9300
TWX: 510-252-0893

Pioneer Electronics
40 Oser Avenue
Hauppauge 11787
Tel: (516) 231-9200

†Pioneer Electronics
60 Crossway Park West
Woodbury, Long Island 11797
Tel: (516) 921-8700
TWX: 510-221-2184

†Pioneer Electronics
840 Fairport Park
Fairport 14450
Tel: (716) 381-7070
TWX: 510-253-7001

NORTH CAROLINA

†Arrow Electronics, Inc.
5240 Greensdale Road
Raleigh 27604
Tel: (919) 876-3132
TWX: 910-928-1855

†Hamilton/Avnet Electronics
3510 Spring Forest Drive
Raleigh 27604
Tel: (919) 878-0819
TWX: 910-928-1836

Pioneer/Technologies Group, Inc.
801 A Southern Pine Blvd.
Charlotte 28210
Tel: (919) 527-8188
TWX: 810-621-0366

OHIO

Arrow Electronics, Inc.
7620 McEwen Road
Centerville 45459
Tel: (513) 435-5583
TWX: 910-459-1611

†Arrow Electronics, Inc.
6238 Cochran Road
Solon 44139
Tel: (216) 248-3990
TWX: 810-427-9409

†Hamilton/Avnet Electronics
954 Senate Drive
Dayton 45459
Tel: (513) 439-6733
TWX: 810-450-2531

Hamilton/Avnet Electronics
4588 Emery Industrial Pkwy.
Warrensville Heights 44126
Tel: (216) 349-5100
TWX: 810-427-9452

†Hamilton/Avnet Electronics
777 Brookside Blvd.
Westerville 43081
Tel: (614) 882-7004

†Pioneer Electronics
4433 Interpoint Boulevard
Dayton 45424
Tel: (513) 236-9900
TWX: 810-459-1622

†Pioneer Electronics
4800 E. 131st Street
Cleveland 44105
Tel: (216) 587-3600
TWX: 810-422-2211

OKLAHOMA

Arrow Electronics, Inc.
1211 E. 51st St., Suite 101
Tulsa 74146
Tel: (918) 252-7537

†Hamilton/Avnet Electronics
12121 E. 51st St., Suite 102A
Tulsa 74146
Tel: (918) 252-7297

OREGON

†Almac Electronics Corp.
1885 N.W. 169th Place
Beaverton 97005
Tel: (503) 629-8090
TWX: 910-467-8746

†Hamilton/Avnet Electronics
6024 S.W. Jean Road
Bldg. C, Suite 10
Lake Oswego 97034
Tel: (503) 635-7848
TWX: 910-455-8179

Wyle Distribution Group
5250 N.E. Elam Young Parkway
Suite 600
Hillsboro 97124
Tel: (503) 640-8000
TWX: 910-460-2203

PENNSYLVANIA

Arrow Electronics, Inc.
650 Seco Road
Monroeville 15146
Tel: (412) 856-7000

Hamilton/Avnet Electronics
2800 Liberty Ave.
Pittsburgh 15238
Tel: (412) 281-4150

Pioneer Electronics
259 Kappa Drive
Pittsburgh 15238
Tel: (412) 782-2300
TWX: 710-795-3122

†Pioneer/Technologies Group, Inc.
Delaware Valley
261 Gibraltar Road
Horsham 19044
Tel: (215) 674-4000
TWX: 910-665-6778

TEXAS

†Arrow Electronics, Inc.
3220 Commander Drive
Carrollton 75006
Tel: (214) 380-6464
TWX: 910-860-5377

†Arrow Electronics, Inc.
10899 Kinghurst
Suite 100
Houston 77099
Tel: (713) 530-4700
TWX: 910-880-4459

†Arrow Electronics, Inc.
2227 W. Braker Lane
Austin 78759
Tel: (512) 835-4180
TWX: 910-874-1348

†Hamilton/Avnet Electronics
1807 W. Braker Lane
Austin 78758
Tel: (512) 837-8911
TWX: 910-874-1319

†Hamilton/Avnet Electronics
2111 W. Walnut Hill Lane
Irving 75038
Tel: (214) 550-6111
TWX: 910-860-5929

†Hamilton/Avnet Electronics
4850 Wright Rd., Suite 190
Stafford 76257
Tel: (713) 240-7733
TWX: 910-881-5523

†Pioneer Electronics
18260 Kramer
Austin 78758
Tel: (512) 835-4000
TWX: 910-874-1323

†Pioneer Electronics
13710 Omega Road
Dallas 75234
Tel: (214) 386-7300
TWX: 910-850-5563

†Pioneer Electronics
5853 Point West Drive
Houston 77036
Tel: (713) 988-5555
TWX: 910-861-1606

Wyle Distribution Group
1610 Greenville Avenue
Richardson 75081
Tel: (214) 235-9953

UTAH

Arrow Electronics
1946 Parkway Blvd.
Salt Lake City 84119
Tel: (801) 973-6913

†Hamilton/Avnet Electronics
1555 West 2100 South
Salt Lake City 84119
Tel: (801) 972-2800
TWX: 910-925-4018

Wyle Distribution Group
1325 West 2200 South
Suite E
West Valley 84119
Tel: (801) 974-9953

WASHINGTON

†Almac Electronics Corp.
14360 S.E. Eastgate Way
Bellevue 98007
Tel: (206) 643-9992
TWX: 910-444-2067

Arrow Electronics, Inc.
19540 68th Ave. South
Kent 98032
Tel: (206) 575-4420

†Hamilton/Avnet Electronics
14212 N.E. 21st Street
Bellevue 98005
Tel: (206) 643-3950
TWX: 910-443-2469

Wyle Distribution Group
15385 N.E. 90th Street
Redmond 98052
Tel: (206) 880-1150

WISCONSIN

Arrow Electronics, Inc.
200 N. Patrick Blvd., Ste. 100
Brookfield 53005
Tel: (414) 767-5600
TWX: 910-262-1193

Hamilton/Avnet Electronics
2975 Moorland Road
New Berlin 53151
Tel: (414) 784-4510
TWX: 910-262-1182

CANADA

ALBERTA

Hamilton/Avnet Electronics
2816 21st Street N.E.
Calgary T2E 6Z3
Tel: (403) 230-3586
TWX: 03-827-642

Zenronics
Bay No. 1
3350 14th Avenue N.E.
Calgary T2A 5J4
Tel: (403) 272-1021

BRITISH COLUMBIA

†Hamilton/Avnet Electronics
105-2550 Boundary
Burnaby V5M 3Z3
Tel: (604) 437-6667

Zenronics
108-11400 Bridgeport Road
Richmond V6X 1T2
Tel: (604) 273-5575
TWX: 04-5077-89

MANITOBA

Zenronics
60-1313 Border Unit 60
Winnipeg R3H 0X4
Tel: (204) 694-1957

ONTARIO

Arrow Electronics, Inc.
35 Anafans Dr.
Nepean K2E 7W5
Tel: (613) 226-6903

Arrow Electronics, Inc.
1093 Meyerside
Mississauga L5T 1M4
Tel: (416) 677-7432
TWX: 06-218213

†Hamilton/Avnet Electronics
6845 Rexwood Road
Units 3-4-5
Mississauga L4T 1R2
Tel: (416) 677-7432
TWX: 010-452-8867

Hamilton/Avnet Electronics
6845 Rexwood Rd., Unit 6
Mississauga L4T 1R2
Tel: (416) 277-0484
†Hamilton/Avnet Electronics
180 Colonnade Road South
Nepean K2E 7L5
Tel: (613) 226-1700
TWX: 05-349-71

†Zenronics
5 Tibury Court
Brampton L6T 3T4
Tel: (416) 651-9600
TWX: 06-976-78

†Zenronics
155 Colonnade Road
Unit 17
Nepean K2E 7K1
Tel: (613) 226-8840

Zenronics
60-1313 Border St.
Winnipeg R3H 0Y4
Tel: (204) 694-7957

QUEBEC

†Arrow Electronics Inc.
4050 Jean Talon Ouest
Montreal H4P 1W1
Tel: (514) 735-5511
TWX: 05-25590

Arrow Electronics, Inc.
500 Avenue St-Jean Baptiste
Suite 280
Quebec G2E 5R9
Tel: (418) 871-7500
FAX: 418-871-6816

Hamilton/Avnet Electronics
2795 Halpern
St. Laurent H2E 7K1
Tel: (514) 335-1000
TWX: 610-421-3731

Zenronics
817 McCaffrey
St. Laurent H4T 1M3
Tel: (514) 737-9700
TWX: 05-827-535



EUROPEAN SALES OFFICES

DENMARK

Intel Denmark A/S
Gjellervej 61, 3rd Floor
2400 Copenhagen NV
Tel: (45) (31) 15 80 33
TLX: 19567

FINLAND

Intel Finland OY
Ruusilantie 2
00390 Helsinki
Tel: (358) 0 544 644
TLX: 123332

FRANCE

Intel Corporation S.A.R.L.
1, Rue Edison-BP 303
78054 St. Quentin-en-Yvelines
Cedex
Tel: (33) (1) 30 57 70 00
TLX: 699016

WEST GERMANY

Intel Semiconductor GmbH*
Domacher Strasse 1
8016 Feldkirchen bei Muenchen
Tel: (49) 089/90992-0
TLX: 5-23177

Intel Semiconductor GmbH
Hohenzollern Strasse 5
3000 Hannover 1
Tel: (49) 0511/344081
TLX: 9-29525

Intel Semiconductor GmbH
Abraham Lincoln Strasse 16-18
6200 Wiesbaden
Tel: (49) 06121/7605-0
TLX: 4-185183

Intel Semiconductor GmbH
Zettachring 10A
7000 Stuttgart 80
Tel: (49) 0711/7287-280
TLX: 7-254826

ISRAEL

Intel Semiconductor Ltd.*
Aldim Industrial Park-Neve Sharet
P.O. Box 43202
Tel-Aviv 61430
Tel: (972) 03-498080
TLX: 371215

ITALY

Intel Corporation Italia S.p.A.*
Milanofori Palazzo E
20090 Assago
Milano
Tel: (39) (02) 89200950
TLX: 341286

NETHERLANDS

Intel Semiconductor B.V.*
Postbus 84130
3099 CC Rotterdam
Tel: (31) 10.407.11.11
TLX: 22283

NORWAY

Intel Norway A/S
Hvamveien 4-PO Box 92
2013 Skjetten
Tel: (47) (6) 942 420
TLX: 76018

SPAIN

Intel Iberia S.A.
Zurbaran, 28
28010 Madrid
Tel: (34) (1) 308.25.52
TLX: 46880

SWEDEN

Intel Sweden A.B.*
Dalvagen 24
171 36 Solna
Tel: (46) 8 734 01 00
TLX: 12261

SWITZERLAND

Intel Semiconductor A.G.
Zuerichstrasse
8185 Winkel-Ruetli bei Zuerich
Tel: (41) 01/850 62 62
TLX: 825977

UNITED KINGDOM

Intel Corporation (U.K.) Ltd.*
Pipers Way
Swindon, Wiltshire SN3 1RJ
Tel: (44) (0793) 696000
TLX: 444447/8

EUROPEAN DISTRIBUTORS/REPRESENTATIVES

AUSTRIA

Bacher Electronics G.m.b.H.
Rottenmuhlgasse 26
1120 Wien
Tel: (43) (0222) 83 56 46
TLX: 31532

BELGIUM

Inelco Belgium S.A.
Av. des Croix de Guerre 94
1120 Bruxelles
Oorlogskruiselaan, 94
1120 Brussel
Tel: (32) (02) 216 01 60
TLX: 6475 or 2090

DENMARK

ITT-Multikomponent
Naverland 29
2600 Glostrup
Tel: (45) (0) 2 45 66 45
TLX: 33 355

FINLAND

OY Fintronic AB
Melkonkatu 24A
00210 Helsinki
Tel: (358) (0) 6926022
TLX: 124224

FRANCE

Almex
Zone industrielle d'Antony
48, rue de l'Aubepine
BP 102
92164 Antony cedex
Tel: (33) (1) 46 56 21 12
TLX: 250067

Jermyn-Generim
60, rue des Gemeaux
Silic 580
94653 Rungis cedex
Tel: (33) (1) 49 78 49 78
TLX: 261585

Metrologie
Tour d'Asnieres
4, av. Laurent-Cely
92606 Asnieres Cedex
Tel: (33) (1) 47 90 62 40
TLX: 611448

Tekelec-Airtronic
Cite des Bruyeres
Rue Caille Vernet - BP 2
92310 Sevres
Tel: (33) (1) 45 34 75 35
TLX: 204552

WEST GERMANY

Electronic 2000 AG
Stahlgruberring 12
8000 Muenchen 82
Tel: (49) 089/42001-0
TLX: 522561

ITT Multikomponent GmbH
Postfach 1265
Bahnhofstrasse 44
7141 Moeglingen
Tel: (49) 07141/4879
TLX: 726472

Jermyn GmbH
Im Dachstueck 9
6250 Limburg
Tel: (49) 06431/508-0
TLX: 415257-0

Metrologie GmbH
Meglingerstrasse 49
8000 Muenchen 71
Tel: (49) 089/78042-0
TLX: 5213189

Proelectron Vertriebs GmbH
Max Planck Strasse 1-3
6072 Dreieich
Tel: (49) 06103/30434-3
TLX: 417903

IRELAND

Micro Marketing Ltd.
Glenageary Office Park
Glenageary
Co. Dublin
Tel: (353) (01) 85 63 25
TLX: 31584

ISRAEL

Eastronics Ltd.
ATD Portugal LDA
P.O. B. 39300
Tel-Aviv 61392
Tel: (972) 03-475151
TLX: 33638

ITALY

Intesi
Divisione ITT Industries GmbH
Viale Milanofori
Palazzo E/5
20090 Assago (MI)
Tel: (39) 02/2440012
TLX: 311351

Lasi Elettronica S.p.A.
V. le Fidio Testi, 126
20092 Cinisello Balsamo (MI)
Tel: (39) 02/2440012
TLX: 352040

Telcom S.r.l.
Via M. Civitali 75
20148 Milano
Tel: (39) 02/4049046
TLX: 335654

ITT Multicomponents
Viale Milanofori E/5
20090 Assago (MI)
Tel: (39) 02/2440012
TLX: 311351

Silverstar
Via Dei Gracchi 20
20146 Milano
Tel: (39) 02/49961
TLX: 332189

NETHERLANDS

Koning en Hartman Elektrotechniek
B.V.
Energieweg 1
2627 AP Delft
Tel: (31) (0) 15/609906
TLX: 38660

NORWAY

Nordisk Elektronikk (Norge) A/S
Postboks 123
Smedsveien 4
1364 Hvalstad
Tel: (47) (02) 84 62 10
TLX: 77546

PORTUGAL

ATD Portugal LDA
Rua Dos Lusíados, 5 Sala B
1300 Lisboa
Tel: (35) (1) 64 80 91
TLX: 61562

Ditram
Avenida Miguel Bombarda, 133
1000 Lisboa
Tel: (35) (1) 54 53 13
TLX: 14182

SPAIN

ATO Electronica, S.A.
Plaza Ciudad de Viena, 6
28040 Madrid
Tel: (34) (1) 234 40 00
TLX: 42477

ITT-SESA
Calle Miguel Angel, 21-3
28010 Madrid
Tel: (34) (1) 419 09 57
TLX: 27461

Metrologia Iberica, S.A.
Ctra. de Fuencarral, n.80
28100 Alcobendas (Madrid)
Tel: (34) (1) 653 85 11

SWEDEN

Nordisk Elektronik AB
Torshamnsgatan 39
Box 36
164 93 Kista
Tel: (46) 08-03 46 30
TLX: 105 47

SWITZERLAND

Industrie A.G.
Heristrasse 31
8304 Wallisellen
Tel: (41) (01) 8328111
TLX: 56785

TURKEY

EMPA Electronic
Lindwurmstrasse 95A
8000 Muenchen 2
Tel: (49) 089/53 80 570
TLX: 528573

UNITED KINGDOM

Accent Electronic Components Ltd.
Jubilee House, Jubilee Road
Leicworth, Herts SG6 1TL
Tel: (44) (0462) 686666
TLX: 826293

Bytech-Cornway Systems
3 The Western Centre
Western Road
Bracknell RG12 1RW
Tel: (44) (0344) 55333
TLX: 847201

Jermyn

Vestry Estate
Offord Road
Sevenoaks
Kent TN14 5EU
Tel: (44) (0732) 450144
TLX: 95142

MMD

Unit 8 Southview Park
Caversham
Reading
Berkshire RG4 0AF
Tel: (44) (0734) 481666
TLX: 846669

Rapid Silicon
Rapid House
Denmark Street
High Wycombe
Buckinghamshire HP11 2ER
Tel: (44) (0494) 442266
TLX: 837931

Rapid Systems
Rapid House
Denmark Street
High Wycombe
Buckinghamshire HP11 2ER
Tel: (44) (0494) 450244
TLX: 837931

YUGOSLAVIA

H.R. Microelectronics Corp.
2005 de la Cruz Blvd., Ste. 223
Santa Clara, CA 95050
U.S.A.
Tel: (1) (408) 988-0286
TLX: 387452

Rapido Electronic Components
S.p.A.
Via C. Beccaria, 8
34133 Trieste
Italia
Tel: (39) 040/360555
TLX: 460461

*Field Application Location



UNITED STATES, Intel Corporation
3065 Bowers Ave., Santa Clara, CA 95051
Tel: (408) 765-8080

JAPAN, Intel Japan K.K.
5-6 Tokodai, Tsukuba-shi, Ibaraki, 300-26
Tel: 029747-8511

FRANCE, Intel Corporation S.A.R.L.
1, Rue Edison, BP 303, 78054 Saint-Quentin-en-Yvelines Cedex
Tel: (33) 1-30 57 70 00

UNITED KINGDOM, Intel Corporation (U.K.) Ltd.
Pipers Way, Swindon, Wiltshire, England SN3 1RJ
Tel: (44) (0793) 696000

WEST GERMANY, Intel Semiconductor GmbH
Dornacher Strasse 1
8016 Feldkirchen bei Muenchen
Tel: (49) 089/90992-0

HONG KONG, Intel Semiconductor Ltd.
10/F East Tower, Bond Center, Queensway, Central
Tel: (5) 8444-555

CANADA, Intel Semiconductor of Canada, Ltd.
190 Attwell Drive, Suite 500
Rexdale, Ontario M9W 6H8
Tel: (416) 675-2105